

TRUE POWER MULTIMETER

Measures True Power Up to 6,000W Plus Voltage and Current



The True Power Multimeter measures true power up to 6,000W plus voltage and current. This unit measures AC watts of loads to 10A and 600V AC, AC and DC voltage to 600V, AC and DC current to 10A. Monitors and evaluates power demands of single phase loads.

FEATURES:

- Measure AC watts of loads to 10A and 600V AC
- Large, easy to read 3-1/2 digit LCD display and clearly labeled front panel controls
- Measure AC voltage to 600V and DC voltage to 600V, AC and DC Current to 10A
- Monitor and evaluate power demands of single phase loads
- Complete with battery and test leads

SPECIFICATIONS:

	Range	Resolution	Accuracy (%rdg+digits)
Watts:	0W to 2000W, 6000W	1W, 10W	+/- (1% + 1d)
AC Voltage (45-60Hz):	0V to 200V, 600V	0.1V, 1V	+/- (0.8% + 1d)
DC Voltage:	0V to 200V, 1000V	0.1V, 1V	+/- (0.8% + 1d)
AC/DC Current:	10A	10mA	+/- (1% + 1d)
Input Voltage/ Current:	0 to 600AC V, 1 to 10AC A		
Overload Protection:	600V		
Input Impedance:	1M Ω		
Dimensions:	7" L x 3.5" W x 1.4" D (180 mm x 80 mm x 35 mm)		
Weight:	1 lb 3 oz (538 g)		

PART NUMBER

DESCRIPTION

M015-024

TRUE POWER MULTIMETER

M015-025

TRUE POWER MULTIMETER WITH NIST

24-HOUR PRODUCT SERVICES

Internet: www.uvprocess.com

E-mail: info@uvps.com



UV PROCESS SUPPLY, INC.